



Order Code 40362
Description DWL 32W 75° C90 IP54 ST RD 3K
Code 103040362
Driver Code 530462000
Current Default (Max) 800 mA
Number of Drivers 1



ADJUSTMENT OF THE POWER OF THE APPLIANCES BY MEANS OF THE DIP SWITCH

Current mA	Power %	Switch Positions			
		1	2	3	4
300	38%	OFF	OFF	OFF	OFF
350	44%	ON	OFF	OFF	OFF
400	50%	OFF	ON	OFF	OFF
450	56%	ON	ON	OFF	OFF
500	63%	OFF	OFF	ON	OFF
550	69%	ON	OFF	ON	OFF
600	75%	OFF	ON	ON	OFF
650	81%	ON	ON	ON	OFF
700	88%	OFF	OFF	OFF	ON
750	94%	ON	OFF	OFF	ON
800	100%	OFF	ON	OFF	ON
850	-	-	-	-	-
900	-	-	-	-	-
950	-	-	-	-	-
1000	-	-	-	-	-
1050	-	-	-	-	-