

## **IRON FLAG**


**Escape sign luminaire in angular design** with housing made of unpainted aluminium and universal display pane made of polycarbonate. Easy to install. 1- or 2-sided escape route indication through exchangeable escape sign foils. Laser module Orma for additional escape route indication (only in emergency operation) through projection of an arrow symbol on the floor for version LIFE available as accessory.

Versions for surface wall and ceiling mounting, bracket and wire pendulum and with additional accessories for recessed ceiling mounting

#### **MOUNTING TYPES**

MOUNTING TYPES WITH ACCESSORIES





#### **TECHNICAL DATA**

Housing: Aluminium, anodized, grey

Display pane: Polycarbonate (display pane)

Polycarbonate (foil, printed)

Service life  $L_{80}B_{20}$ : 50.000 h

Color stability: 3 SDCM
Color temperature: 4.000 K
Color rendering index: 80
Optic interface: LIFE











**Commissioning:** For <u>Autotest</u>, operating duration, operating mode PS, monitoring group and test duration are only programmable per app B.connect over smartphone locally on luminaire.

## **SELF-CONTAINED SUPPLY**

**Mains supply:** 198 V - 254 V/50 Hz

Switching: Maintained and

non-maintained

Ambient temperature:  $-10~^{\circ}\text{C}$  to  $+45~^{\circ}\text{C}$ 

Protection class:

### **DECENTRAL SUPPLY**

Ambient temperature: -20 °C to +40 °C

Protection class:


# **CENTRAL SUPPLY**


Mains supply:198 V - 254 V/50 HzBattery supply:176 V - 276 VAmbient temperature:-20 °C to +40 °C


Protection class:


Mains supply (alt.): 90 V - 254 V / 50/60 HzBattery supply (alt.): 90 V - 276 V

Surface wall mounting









## LIFE SELF-CONTAINED SUPPLY

Autotest / CableCom Order code	Logica Order code	Logica FM Order code	<b>₹♥</b>	LED	t	<u> </u>	S~
Surface wall mounting (1-si	ded escape route indication)	, surface ceiling mounting or	r bracket (2-sid	ded escape r	oute indication)¹		
19810	19810+15036 <sup>2</sup>	19810+15049 <sup>2</sup>	20 m	24	1 h / 3 h / 8 h	LIFE 6.4 V / 0.6 Ah	8 VA
19811	19811+15036 <sup>2</sup>	19811+15049 <sup>2</sup>	30 m	36	1 h / 3 h / 8 h	2x LIFE 6.4 V / 0.6 Ah	8 VA
Wire pendulum (2-sided esc	cape route indication)						
19812	19812+15036 <sup>2</sup>	19812+15049 <sup>2</sup>	20 m	24	1 h / 3 h / 8 h	LIFE 6.4 V / 0.6 Ah	8 VA

30 m

الم المالية ا	ECENTRAL SUPPLY
---	-----------------

19813

19813+15036<sup>2</sup>

Sicuro24 Order code	<b>₹ •</b>	LED	P=
Surface wall mounting (1-sided escape route indicati surface ceiling mounting or bracket (2-sided escape		on)¹	

19813+15049<sup>2</sup>

17894	20 m	24	2.5 W
17895	30 m	36	3.7 W
Wire pendulum (2-sided escape route indication)			
17896	20 m	24	2.5 W
17897	30 m	36	3.7 W



 $<sup>^{2}</sup>$  Please order Logica interface (15036) and Logica FM interface (15049) separately.



1 h / 3 h / 8 h


Sicuro230 Order code	_	<b>₹</b> ₩	LED o o	S~	P=

2x LIFE 6.4 V / 0.6 Ah

8 VA

Surface wall mounting (1-sided escape route indication), surface ceiling mounting or bracket (2-sided escape route indication)<sup>1</sup>

17890	20 m	24	6.1 VA / 2.6 W
17891	30 m	36	8.3 VA / 4.1 W
Wire pendulum (2-sided escape route indica	ation)		
17892	20 m	24	6.1 VA / 2.6 W
17893	30 m	36	8.3 VA / 4.1 W



Incldued in scope of delivery					
Order code		Description			
VD 20 m	VD 30 m				
-	-	Set of escape sign foils	<b>♥ ₹ ₹ ₹ ₹ ₹</b>		

Please orde	r accessories s	eparately
Order code		Description
VD 20 m	VD 30 m	
15036	15036	Logica interface for LIFE
15049	15049	Logica FM interface for LIFE (IP65, luminaire attachment)
15038	15038	DALI interface for LIFE (for connection to DALI central of the general and safety lighting)
19880	19881	Recessed mounting set for hollow ceilings (only for surface ceiling mounting)
19885	19886	Recessed mounting set for hollow ceilings (only for wire pendulum)
19884	19884	Laser module Orma for LIFE